




Vario series is exactly the same like the Longlife series, but it is a module based, so you have to have external power source. Either a battery or adapter.



Number settings:  
If your initial SMS settings does not work, try the following combinations



## QUICK SET-UP GUIDE:

### IMPORTANT

■ IT WAS NOT DEVELOPED FOR 220v CONTINUOUS USAGE

### DIODE FLASHING SIGNALS:

#### 1. TURN ON THE DEVICE

1. Carefully open the SIMCARD slot and place the SIMCARD inside.



2. Insert a SIM card with the pin code switched off or a memory card into the device.

3. Hold down the power button for 5 seconds (the LEDs will turn on)

#### 2. CALL FUNCTION

1. **Set the master number of your mobile phone by SMS (+#your phone number#)**

3. Dial the units number.

4. The device answers the call and then it is possible to listen to surroundings.

5. To call back, send an SMS 333 to the device number. When the volume exceeds 60dB, the device will call the pre-set master number.

## SMS COMMANDS

Setting the master number of the unit		+#phone number# Ex. 000#606053025#
Sound detection	222	When it exceeds 60dB, it records 10 minutes of audio on the memory card
Callback	333	When exceeding 60dB, it calls the set master number
Disable all functions	555	Cancels all set functions
Sms vibration detection	666	It sends an SMS to the master number in case of vibration detection
Call vibration detection	777	Calls the master number if vibration is detected
Sending a location	999	Sends the current location via SMS
Password reset	pwrst	Resets the set password
Factory reset	1122	Resets the device to factory settings
Imei check	Imei#	Displays the device's imei
Restart the device	SYSRST#	Restarts the device
LED on / off	LED#on / LED#off	Turns on the diode Turns off the diode

## PACKAGE CONTENT

1. Vario module
2. Cable
3. 3M Sticker for easier placement

## USEFUL INFORMATION

You can connect several of VARIO units to a 12V battery, using our special convertor, which can be purchased via the [www.stealthtronic.com](http://www.stealthtronic.com) website.

## DISCLAIMER

This user manual can be slightly different from specific product. Before start using the device, check your local legal terms. Neither supplier nor distributor don't assume and responsibility for using device in conflict with local law.